


C1273a (GN)

9D930

A407
Glow plug control
module (GPCM)




F07101

Pin	Circuit	Circuit function
1	110 (BN/WH)	Glow plug 5, control
2	110 (BN/RD)	Glow plug 7, control
3	380 (BK/OG)	Battery Power
4	–	not used
5	–	not used
6	110 (BN/BU)	Glow plug 1, control
7	110 (BN/GN)	Glow plug 3, control
8	1086 (VT/OG)	Powertrain Control Module (PCM) (12A650)
9	1277 (WH/LG)	Powertrain Control Module (PCM) (12A650)

C1273b (BK)

9D930

A407
Glow plug control
module (GPCM)




F07101

Pin	Circuit	Circuit function
1	110 (YE/WH)	Glow plug 6, control
2	110 (YE/RD)	Glow plug 8, control
3	380 (BK/OG)	Battery Power
4	–	not used
5	–	not used
6	110 (YE/BU)	Glow plug 2, control
7	110 (YE/GN)	Glow plug 4, control
8	–	not used
9	361 (RD)	PCM power relay, fused feed


C1278

12A581



F03169

13A006



F03289